



Program SMA with Bond Sidekick (Gen. 2) Wireless Wall Switch (Models 9300, 5100, 8000, 9600)

Step 1: Select the desired channel(s) on the Bond Sidekick switch for the SM Automatic motor. Multiple channels may be programmed to SMA at the same time.

Note: By default, the Bond switch is configured to Somfy RTS motors.

Step 2: Using the included tool, quick press and release the Menu button on the back of the Bond switch. Ensure the Stop LED light blinks for 5 seconds.

Step 3: After blinking Press the following 4 buttons:

1 → 3 → 1 → ■ (STOP)

Step 4: The selected channel(s) for the SMA motor will blink to confirm change. Next follow the instructions to sync the Bond switch with SMA line voltage motors (9300, 9600, 5100, 8000).

Syncing Bond Sidekick with SM Automatic Motors (9300, 9600, 5100, 8000)

Step 1: Using the existing Ti-RF remote, press and hold the “stop” button for 5 seconds until the receiver beeps.

Step 2: The receiver will beep for 10 seconds while in pairing mode.

Step 3: Select the desired channel on the Bond Sidekick and Press the “UP” arrow. 3 quick beeps confirm pairing. *Multiple SMA motors can be synced to the same channel.*

Step 4: Enjoy your Bond Sidekick and SM Automatic motor.