

How to set limits on a Model 400 series Drapery Motor

These instructions will explain how to set limits on an SM Automatic 400 series drapery motor.

These instructions will use limit setting switch, however, a wall switch, or a wireless transmitter and receiver can also be used.

1. Plug the drapery motor into a standard 110 volt outlet.
2. Plug the limit setting switch into either of the two modular ports, located on the bottom of the motor.
3. Push the open button on the switch, and allow the drapery to open completely.
4. Push the close button, and allow the drapery to close completely.
5. If the motor stops before reaching the end of the track, push the close button 2 times.
6. The motor will then run to the full close position.
7. Now push the open button, and allow the drapery to open completely.
8. The drapery motor limits are now set.

To watch a video demonstration of this procedure, please view [Instructional Video #1](#).